


MALE NPT CONNECTOR



PART No.	A Tube OD	Hex Tube Nut	D	T NPT	E Min Orifice	F	L OAL	Hex Body
DCT-1-1-*	1/16"	5/16"	0.44	1/16"	0.05	0.79	0.94	5/16"
DCT-1-2-*	1/16"	5/16"	0.44	1/8"	0.05	0.85	1.00	7/16"
DCT-2-1-*	1/8"	7/16"	0.60	1/16"	0.09	0.91	1.17	7/16"
DCT-2-2-*	1/8"	7/16"	0.60	1/8"	0.09	0.91	1.17	7/16"
DCT-2-4-*	1/8"	7/16"	0.60	1/4"	0.09	1.12	1.39	9/16"
DCT-3-2-*	3/16"	1/2"	0.63	1/8"	0.12	0.94	1.21	7/16"
DCT-3-4-*	3/16"	1/2"	0.63	1/4"	0.12	1.16	1.43	9/16"
DCT-4-1-*	1/4"	9/16"	0.70	1/16"	0.19	1.00	1.30	1/2"
DCT-4-2-*	1/4"	9/16"	0.70	1/8"	0.19	1.00	1.30	1/2"
DCT-4-4-*	1/4"	9/16"	0.70	1/4"	0.19	1.19	1.49	9/16"
DCT-4-6-*	1/4"	9/16"	0.70	3/8"	0.19	1.22	1.52	11/16"
DCT-4-8-*	1/4"	9/16"	0.70	1/2"	0.19	1.44	1.76	7/8"
DCT-4-12-*	1/4"	9/16"	0.70	3/4"	0.19	1.47	1.77	11/16"
DCT-5-2-*	5/16"	5/8"	0.73	1/8"	0.25	1.05	1.35	9/16"
DCT-5-4-*	5/16"	5/8"	0.73	1/4"	0.25	1.23	1.53	9/16"
DCT-6-2-*	3/8"	11/16"	0.76	1/8"	0.28	1.09	1.39	5/8"
DCT-6-4-*	3/8"	11/16"	0.76	1/4"	0.28	1.28	1.57	5/8"
DCT-6-6-*	3/8"	11/16"	0.76	3/8"	0.28	1.28	1.57	11/16"
DCT-6-8-*	3/8"	11/16"	0.76	1/2"	0.28	1.50	1.80	7/8"
DCT-6-12-*	3/8"	11/16"	0.76	3/4"	0.28	1.54	1.83	11/16"
DCT-8-4-*	1/2"	7/8"	0.86	1/4"	0.28	1.31	1.72	13/16"
DCT-8-6-*	1/2"	7/8"	0.86	3/8"	0.41	1.31	1.72	13/16"
DCT-8-8-*	1/2"	7/8"	0.86	1/2"	0.41	1.50	1.91	7/8"
DCT-8-12-*	1/2"	7/8"	0.86	3/4"	0.41	1.54	1.94	11/16"
DCT-8-16-*	1/2"	7/8"	0.86	1"	0.41	1.87	2.28	13/8"
DCT-10-6-*	5/8"	1"	0.86	3/8"	0.41	1.34	1.74	15/16"
DCT-10-8-*	5/8"	1"	0.86	1/2"	0.50	1.54	1.94	15/16"
DCT-10-12-*	5/8"	1"	0.86	3/4"	0.50	1.53	1.94	11/16"
DCT-12-8-*	3/4"	11/8"	0.86	1/2"	0.50	1.59	2.00	11/16"
DCT-12-12-*	3/4"	11/8"	0.86	3/4"	0.62	1.59	2.00	11/16"
DCT-12-16-*	3/4"	11/8"	0.86	1"	0.62	1.87	2.28	13/8"
DCT-14-12-*	7/8"	11/4"	0.86	3/4"	0.72	1.59	1.99	113/16"
DCT-16-8-*	1"	11/2"	1.04	1/2"	0.50	1.77	2.27	13/8"
DCT-16-12-*	1"	11/2"	1.04	3/4"	0.72	1.77	2.27	13/8"
DCT-16-16-*	1"	11/2"	1.04	1"	0.88	1.97	2.46	13/8"

* Add Suffix "SS" for 316 Stainless Steel or "B" for Brass.

Dimensions are provided in inches and are for reference only, subject to change. Dimensions shown are with the nut in the finger-tight position.