

# RT250 GFCI RECEPTACLE TESTER WITH LCD

For use with North American  
3-wire 120V Electrical Outlets

Easy-to-read LCD  
display shows

- Voltage
- Wiring-faults
- GFCI Trip Time



Featuring patent pending  
detection of Open Neutral  
Open Ground wiring fault



CAT II  
135V

**KLEIN  
TOOLS**



1.800.561.8187

www.**itm**.com

information@itm.com



# RT250 GFCI RECEPTACLE TESTER WITH LCD

The RT250 is an electrical receptacle tester that tests the wiring conditions at an electrical outlet and inspects GFCI devices. The LCD displays the voltage, identifies the wiring fault, and the time required to trip a GFCI device. It is designated for use with North American 3-wire 120V electrical outlets.

Test trip time of  
ground fault circuit  
interrupter

For use on 3-wire, North  
American 120V electrical  
outlets only

**Auto-Hold** is convenient  
for hard-to-reach outlets.  
Simply remove tester to  
view the reading.

**Large readout** clearly  
displays voltage and  
GFCI trip time

**Large backlit  
LCD display** shows  
clear indication of  
wiring conditions

**GFCI button** initiates a  
ground fault. The  
voltage and trip time  
readings alternate in  
the display.

**Bright green and  
red LEDs** illuminate  
for visual indicators

**Low battery  
indicator.**  
Tester comes with  
2x AAA batteries;  
compartment is  
on back.

**Power button;** tester auto-powers  
off after 3 minutes of inactivity to  
conserve battery life.

## WIRING CONDITIONS

- Wired Correctly
- Open Ground
- Open Neutral
- Open Hot
- Dual Open (Neutral & Ground)  
Patent Pending
- Reversed Hot/Ground
- Reversed Hot/Neutral

## CLEAR INDICATION OF VOLTAGE AND WIRING CONDITIONS



For Professionals  
SINCE 1857™

Cat. No.	UPC	Description	Batteries Included	Height	Length	Width	Weight
RT250	0-92644+ 69321-2	GFCI Receptacle Tester with LCD	2x AAA	1.1" ( 2.79 cm)	4.5" (11.4 cm)	2.0" (5.1 cm)	4.8 oz (136 g)



1.800.561.8187

www.itm.com

information@itm.com